

RT106 Extra Big and Loud Waterproof Countdown Timer

Adjustable Alarm Volume

Press  to select the desired alarm volume from 1 to 4.

Set the Timer

Values on the timer are displayed in the hr:min:sec format.

With reference to the following examples, set the desired countdown times.

Press STOP/CLEAR to clear the display before setting new values

To set 12 seconds = press 1, 2

To set 12 minutes = press 1,2,0,0

To set 12 hours = press 1,2,0,0,0,0

To set 12 hours, 12 minutes = press 1,2,1,2,0,0

To set 12 hours, 12 minutes, 12 seconds = press 1,2,1,2,1,2

Start the Countdown Timer

Press START/MEMO to begin the countdown.

When the timer reaches 00:00:00, the alarm will sound.

Press any button to stop the alarm.

Memory

The timer will retain the last value entered in memory. The value is kept until replaced by another value.

Press START/MEMO to recall the value.

Press STOP/CLEAR to clear the display. This does not erase the value from memory.

Battery Installation

Replace the batteries if the LCD display becomes dim.

1. Remove the screw on the battery cover on the back of the timer.
2. Remove the cover, being careful not to dislodge the rubber gasket.
3. Replace the batteries in the cover with two AAA 1.5 volt batteries, observing the correct polarity.
4. Replace the gasket and cover, and secure the screw.

Care and Cleaning

If the timer will not be used for an extended period of time, remove the batteries to prevent battery leakage.

Be sure the battery cover and gasket are tightened securely after replacing the battery, otherwise the timer's water resistance may be affected.

Do not expose to temperatures over 104°F / 40°C.

Not submersible.

Specifications

Countdown Range	99 hours 99 minutes 99 seconds
Display Resolution	1 second
Alarm Sound Volume	90db at 300mm
Alarm Volume Control	Adjustable in 4 steps
Water Resistance	IP65
Battery	Type AAA, 1.5 volts x 2 pieces
Display Size	2.5 (W) x 0.9 (H) inches 65 (W) x 22 (H) mm
Product Size	3.4 (W) x 5.1 (H) x 0.9 (D) inches 88 (W) x 130 (H) x 22 (D) mm
Ambient Operating Temperature	32 to 104°F / 0 to 40°C



ThermoWorks

Utah, U.S.A.

Ph: 801-756-7705

Fax: 801-756-8948

www.thermoworks.com



RT106 Extra Big & Loud Timer



Made in China